

Pioneer Dj



DJM-900nexus DIGITAL MIXER

High fidelity sound card / Six stunning sound colour FX / Overhauled Beat Effects / rekordbox™ Quantize button / Touch sensitive X-PAD / TRAKTOR™ certified / PRO DJ functionality via LAN connection / High performance channel faders / DVS software control / Input switcher / 3-band EQ and 3-band isolator / Fully MIDI assignable

Introducing the DJM-900nexus: the next generation mixer that delivers ultimate computer connectivity, up-to-date effects, high performance features and powerful sound.

Main specifications

Number of channels	4 audio channels, 2 mic channels
Input ports	CD/LINE×6 (RCA), PHONO×2 (RCA) DIGITAL IN×4 (COAXIAL) MIC×2 (front-panel XLR & 1/4 inch JACK dual purpose×1, 1/4 inch JACK×1)
Output ports	MASTER OUT×2 (RCA×1, XLR×1) BOOTH OUT×1 (1/4 inch JACK) HEADPHONE MONITOR OUT×1 (top surface 1/4 inch JACK×1) REC OUT×1 (RCA) DIGITAL OUT×1 (COAXIAL)
Other ports	SEND×1 (1/4 inch JACK), RETURN×1 (1/4 inch JACK) MIDI OUT×1 (5-Pin DIN), USB B port×1, LINK port×1 (RJ45)
Sampling rate	96 kHz
D/A converter	32-bit
A/D converter	24-bit
Frequency response	20 Hz - 20 kHz
Total Harmonic Distortion ratio	0.004% or less
S/N ratio	107 dB or greater (LINE)
Head room	19 dB
Power source	AC 220 ~ 240V (50 Hz/60 Hz)
Power consumption	42 W
Maximum dimensions	331 mm (W) × 409 mm (D) × 108 mm (H)
Unit weight	7.1 kg



Pioneer Europe N.V. Multimedia Division, Slough SL2 4QP, UK TEL +44 (0) 1753 789789

Features and specifications of the products described or illustrated in this catalogue are correct at the time of printing but could change as production changes might occur. This catalogue may contain typographical errors and the colours of the depicted products may deviate slightly from reality. Consult your Pioneer dealer to ensure that actual features and specifications match your requirements. This catalogue may contain references to products that may or will not be available in your country.